

ChamSys

bringing innovation and technology to lighting design



MagicQ PC Wing

USB Connection to PC or Mac

Windows, Linux or OSX

Programming & Playback Buttons

8 Encoders, 12 Faders

2 Direct DMX Outputs

Dimmable LED Desk Lamp

32 Universes

202 Playbacks

Quick and Easy to Programm

Fully Featured Theatre Stacks

Advanced Media Server Support

In-built Media Engine

Fixture Morphing & Cloning

LED Pixel Mapping

Audio Visual Lighting bvba

D' Helst 21 - 9280 Lebbeke - Belgium

Tel. +32-(0)52-412924 - Fax +32-(0)52-412530 - E-mail: info@avl.be

www.avl.be - www.chamsys.be



MagicQ PC Wing



MagicQ PC Wing

- USB Connection to PC or Mac
- Windows, Linux or OSX
- Programming & Playback Buttons
- 8 Encoders, 12 Faders
- 2 Direct DMX Outputs
- Dimmable LED Desk Lamp
- 18 Universes

The MagicQ PC Wing is an extremely powerful USB control wing for connecting to your PC or Mac to control lighting, video and LED with the MagicQ PC software. MagicQ PC software runs under Windows, Linux or OSX. MagicQ PC software is free and uniquely the outputs are fully enabled, allowing you to run shows on up to 18 Universes.

The MagicQ PC Wing enables advanced show programming and playback through real faders, buttons and encoder wheels. The MagicQ PC wing enables easy access to moving light parameters via the 8 rotary encoders, and live show control through the 10 playback faders and cue stack control buttons. In addition there are 2 fully patchable direct DMX outputs on the rear panel.

MagicQ is simple and easy to program, enabling really quick setup - you can be up and running your show in seconds. With unrivalled live editing and live timing options, impressive changes can be made live at the touch of a button - no need to spend hours programming complex effects.

The MagicQ PC software is the same software that MagicQ consoles run - enabling familiar and flexible GUI lighting control, media server connectivity options and in-built media server for LED grid arrays. And with the ability to transfer your show to other MagicQ consoles over the network or using standard USB memory sticks the MagicQ PC Wing can be used as a powerful off-line show editor or back-up system.

The MagicQ PC Wing provides an immensely powerful PC based console in a compact size. Ideal for use by touring Lighting Designers, or for installing into theatres, clubs, and venues, the MagicQ PC Wing is the PC solution of choice for controlling lighting, video and LED.

Features

Tracking / non-tracking option
Fixture, FX and gel library
In-built fixture editor
In-built media engine
LED pixel mapping
Fixture morphing and cloning
Rainbow colour picker (CMY, RGB, HSI)
Individual fade times on any channel
Easy fanning of parameters and times
Configurable faders - HTP, LTP, speed, size, masters
Theatre mark cues, split fades and inhibit masters
Client/server network architecture
Multiple console playback tracking
In-built web server
Remote console control
Visualiser support (including patch transfer)
Architectural zoning and day/date support
MIDI & SMPTE option
Optional Flight Case

Specification

Universes: 32
Channels: 16384
Number of fixtures: Up to 16384
Cues: 5000
Cue Stacks: 1000
Palettes: 3096
Groups: 500
Media Server support: 50 (each different content)

Encoders: 8
Faders: 12
Buttons: 64
Direct DMX512 ports: 2
Dimmable LED console lamps: 1
Remote trigger input: 1
Security lock fixing: 1
Choice of colours: Blue
Universal Power Supply: 110 to 240 VAC

Width: 560mm
Depth: 245mm
Height: 58mm
Weight: 4kg

Product Codes

0200-0001 MagicQ PC Wing
0100-0001 Flight Case for MagicQ PC Wing
0300-0014 Padded Bag for MagicQ PC Wing

All pictures are for information only. Products, specifications and timescales subject to change without notice.

AVL Copyright © 2011

