



# ChamSys

bringing innovation and technology to lighting design



## MagicQ PC Wing

USB Connection to PC or Mac  
Windows, Linux or OSX  
Programming & Playback Buttons  
8 Encoders, 12 Faders  
2 Direct DMX Outputs  
Dimmable LED Desk Lamp  
18 Universes

202 Playbacks  
Quick and Easy to Programm  
Fully Featured Theatre Stacks  
Advanced Media Server Support  
In-built Media Engine  
Fixture Morphing & Cloning  
LED Pixel Mapping

# MagicQ PC Wing



The MagicQ PC Wing is an extremely powerful USB control wing for connecting to your PC or Mac to control lighting, video and LED with the MagicQ PC software. MagicQ PC software runs under Windows, Linux or OSX. MagicQ PC software is free and uniquely the outputs are fully enabled, allowing you to run shows on up to 18 Universes.

The MagicQ PC Wing enables advanced show programming and playback through real faders, buttons and encoder wheels. The MagicQ PC Wing wing enables easy access to moving light parameters via the 8 rotary encoders, and live show control through the 10 playback faders and cue stack control buttons. In addition there are 2 fully patchable direct DMX outputs on the rear panel.

MagicQ is simple and easy to program, enabling really quick setup - you can be up and running your show in seconds. With unrivalled live editing and live timing options, impressive changes can be made live at the touch of a button - no need to spend hours programming complex effects.

The MagicQ PC software is the same software that MagicQ consoles run - enabling familiar and flexible GUI lighting control, media server connectivity options and in-built media server for LED grid arrays. And with the ability to transfer your show to other MagicQ consoles over the network or using standard USB memory sticks the MagicQ PC Wing can be used as a powerful off-line show editor or back-up system.

The MagicQ PC Wing provides an immensely powerful control PC based console in a compact size. Ideal for use by touring Lighting Designers, or for installing into theatres, clubs, and venues, the Maxi Wing is the PC solution of choice for controlling lighting, video and LED.

## Specification

Universes	18
Channels	9216
Number of fixtures	Up to 9216
Cues	5000
Cue Stacks	2000
Palettes	3096
Groups	1000
Numbers of shows	Virtually unlimited
Media Server support	50 (each different content)
Encoders	8
Faders	12
Buttons	64
Direct DMX512 ports	2
Dimmable LED console lamps	1
Remote trigger input	1
Security lock fixing	1
Choice of colours	Blue
Power input	PSU 110 to 240 VAC
Width	560mm
Depth	245mm
Height	58mm
Weight	4kg


## Features

Tracking / non-tracking option  
 Fixture, FX and Gel Library  
 In-built Fixture Editor  
 In-built Media Engine  
 LED pixel mapping  
 Fixture morphing and cloning

Rainbow colour picker (RGB, HSI)  
 Individual fade times on any channel  
 Easy fanning of parameters and times  
 Configurable faders - HTP, LTP, speed, size, masters  
 Theatre mark cues, split fades and inhibit masters

Client/Server network architecture  
 Multiple console Playback Tracking  
 In-built Web Server  
 Remote console control  
 Visualiser support (including patch transfer)  
 Architectural Zoning and Day/Date support

MIDI & SMPTE option  
 Optional Flight Case or Padded Bag



www.chamsys.be

Tel: +32 (0)52 412924 Fax: +32 (0)52 412530 E-mail: info@avl.be  
 Audio Visual Lighting bvba, D'Helst 21, 9280 Lebbeke - Belgium